

MCV2 R00 Dual V.35 cable – Product Code XP8928

Compatible with the FarSync T2P cards

This dual port cable is used to connect both ports of the FarSync T2P to network connections requiring V.35 interfaces.

The label on the cable should read: **MCV2 R00**

Construction

The cable assembly shall have one end of each of two lengths of cable terminated in a 37-Way D-Type male plug and the other ends each terminated in a MRAC-34 plug (ISO 2593).

The overall length of the cable assembly (DB37 to MRAC-34) should be 1.5 metres.

Signal Connections

Interface Signal Name	DB 37-Way Male Contact	MRAC-34 Way Contact	Twisted Pairs	MRAC-34 Connector
ATXa	20	P	PAIR	P O R T A
ATXb	2	S		
ASV35a / TXCA	29	Y	PAIR	
ASV35b	12	AA		
ARXa / RXDA	22	R	PAIR	
ARXb	4	T		
ASa / RXCA	24	V	PAIR	
ASb	6	X		
RTSA	15	C		
A1a / CTSA	23	D		
DTRA	19	H		
DCDA	25	F		
GNDA	37	B		
SHIELD	1	A		
BTXa	26	P	PAIR	P O R T B
BTXb	7	S		
BSV35a / TXCB	30	Y	PAIR	
BSV35b	34	AA		
BRXa / RXDB	27	R	PAIR	
BRXb	9	T		
BSa / RXCB	32	V	PAIR	
BSb	11	X		
RTSB	18	C		
B1a / CTSB	28	D		
DTRB	36	H		
DCDB	35	F		
GNDB	37	B		
SHIELD	1	A		
CABLE SENSE	LINK - DB37-Pin 13 to DB37-Pin 31			